


K2 Media Client Quick Start Guide

For SD-only models

Before you begin, unpack the following items...




...and locate the documentation you need.

Documentation path to install K2 Media Clients with internal storage



Documentation path to install K2 Media Clients with (external) K2 Storage System




1. Make cable connections and, if necessary, configure network

Quick Start networking options

DHCP - By default the K2 Media Client is DHCP enabled and has the chassis serial number as hostname. If supported by your network, you can use these defaults without configuring network settings.

Network configuration - If necessary, configure network settings as follows:

- Connect keyboard, mouse, monitor.
- Logon with the default Windows administrator account:
 - Username: administrator
 - Password: adminK2
- In Windows Network Connections, look in the Device Name column to find **TEAM : Control Team** and configure the control network connection.



2. Power on

- 1 Press bezel-release buttons and flip down front bezel.
- 2 Identify the following: Power LED, Service LED, Serial number, Standby switch
- 3 Press the standby switch to power on.

Normal startup sequence

Power LED goes on and stays on. Service LED stays off. Startup processes complete in approximately two minutes and the K2 Media Client is ready for remote connection and operation.

Note: Add external storage models to a K2 Storage System before proceeding.

3. Install control point software

Note: You can skip ahead if you are:

- Using the Grass Valley control point PC. Skip to step 4.
- Accessing the K2 Media Client locally only. Skip to step 5.

- 1 Choose a network-connected PC as your control point.
- 2 Insert CD, open the *Control Point* folder and run *setup.exe*.
- 3 Follow on-screen instructions, clicking **Next**, **Install**, and **Finish**.

PC System requirements

Microsoft Windows XP Professional, Service Pack 2

Pentium 4 or higher class processor, 2 GHz or greater

Minimum 512 MB RAM, 1 GB recommended

400 MB hard disk space

Graphics acceleration with at least 128 MB memory

Microsoft .NET Framework 1.1 (on CD)

4. Make remote connection

- Control point PC**
- 1 Open the AppCenter shortcut.
 - 2 Logon to AppCenter with the default K2 administrator account.
 - Username: K2admin
 - Password: K2admin
 - 3 Click **Add**.
 - 4 Enter the K2 Media Client hostname or IP address. The default hostname is the chassis serial number (e.g. K2-01AA00015). Refer to Step 2 Power on.
 - 5 Click **OK**.
 - 6 Select the channels to control from this control point PC.
 - 7 Click **OK** and **OK** to save settings and close.

Continue with Quick Start procedures on the reverse side.

5. Configure channels

- 1 Open AppCenter, if it is not already open, and logon with the default K2 administrator account (Username: K2admin, Password: K2admin).
- 2 Click **System | Configuration**.

Bi-directional channels
Each channel tab has input (record) channel settings as well as output (play) channel settings. Configure the settings that apply to your intended use (play and/or record) of the channel.

- 3 Click tabs, buttons, and scroll bar to locate settings.
- 4 Select from drop-down lists to make settings.
- 5 Click **OK** and **Yes** to save settings..

Find commonly modified settings...

And configure as follows:

- | | |
|---|---|
| System → Video Standard: | Select NTSC or PAL . Restart to put change into effect. |
| Channel → C n → Audio input type: | Select AES/EBU or Embedded . |
| Channel → C n → Audio output: | Embedded output group(s): Select Group 1 & 2 or Group 3 & 4 . |
| Channel → C n → Video output timing: | Set Frame , Line , and Sample offset. |

6. Record a clip

- 1 Select a channel
- 2 Select the Recorder application
- 3 Adjust audio
- 4 Begin record
- 5 Stop record
- 6 Rename clip

Bi-directional channels
A channel becomes an input channel when you select a Recorder application. The same channel becomes an output channel when you select a Player or Playlist application.

Timecode for Record
On the AppCenter menu, click **Recorder | Options**. On the Options dialog box click **Timecode** and select **VITC**, **LTC**, or **Internal** timecode for recording and display.

Click again to close the audio control

Use keyboard or on-screen keypad.

Refer to the AppCenter Help menu for complete operating instructions.


7. Play a clip

- 1 Select a channel
- 2 Select the Player application
- 3 Drag a clip into the play channel
- 4 Play the clip
- 5 Eject the clip


Refer to the AppCenter Help menu for complete operating instructions.

8. For more information...

In AppCenter, click **Help | AppCenter Help Topics** and read the complete documentation for operating and configuring K2 Media Client channels.




Find the complete documentation set for K2 products on the Documentation CD:



- User Guide
- System Guide
- Service Manual
- Storage System Manual
- RAID Instruction Manuals

Go to <http://www.thomsongrassvalley.com/support> and search the FAQ Knowledge Bank.



Use the following information to contact product support by phone during business hours. Afterhours phone support is available for warranty and contract customers.

United States	(800) 547-8949 (Toll Free)	France	+33 (1) 34 20 77 77
Latin America	(800) 547-8949 (Toll Free)	Germany	+49 6155 870 606
Eastern Europe	+49 6155 870 606	Greece	+33 (1) 34 20 77 77
Southern Europe	33 (1) 34 20 77 77	Hong Kong	+852 2531 3058
Middle East	+33 (1) 34 20 77 77	Italy	+39 06 8720351
Australia	+61 1300 721 495	Netherlands	+31 35 6238421
Belgium	+32 2 3349031	Poland	+49 6155 870 606
Brazil	+55 11 5509 3440	Russia	+49 6155 870 606
Canada	(800) 547-8949 (Toll Free)	Singapore	+656379 1390
China	+86 106615 9450	Spain	+34 91 512 03 50
Denmark	+45 45968800	Sweden	+46 87680705
Dubai	+971 4 299 64 40	Switzerland	+41 (1) 487 80 02
Finland	+35 9 68284600	UK	+44 870 903 2022



Copyright © 2005 Grass Valley, Inc.
071-8453-00 November 18, 2005